

Autoranging DMM

Autoranging Digital Multimeter Displays 3200 Counts on Super Large 1" LCD Display with Bargraph

Features :

- Functions include DC/AC Voltage and Current, Resistance, Capacitance, Frequency plus Diode/Transistor/Audible Continuity tests
- Auto or manual ranging with Data Hold
- Display 3200 counts with 2-3 updates per second
- 0.8% basic DC voltage accuracy
- Overrange, Polarity, and Low Battery indications
- Designed to meet IEC 1010 standards
- Four Input Jacks with Overload and current fuse protection
- Rotary switch selects functions and 29 ranges
- Complete with test leads, 9V battery, and protective holster



Specifications

	Range
DC Voltage:	320mV, 3.2V, 32V, 320V, 1000V
AC Voltage:	3.2V, 32V, 320V, 750V
DC Current:	300mA, 3200mA, 32mA, 320mA, 10A
AC Current:	300mA, 3200mA, 32mA, 320mA, 10A
Resistance (Ω):	320, 3.2K, 32K, 320K, 3.2M, 30M
Capacitance:	320nF, 32mF
Frequency:	32kHz to 200kHz
Dimensions/Weight:	7x3.3x1.3" (178x83x34mm) / 7.1oz. (250g)

Basic Accuracy (%rdg+digits)

DC Voltage:	±(0.25%+1d)
AC Voltage:	±(1%+5d)
DC Current:	±(1%+2d)
AC Current:	±(1.5%+2d)
Resistance (Ω):	±(1.2%+2d)
Capacitance:	±(3%+5d)
Frequency:	±(1.2%+3d)

380771 Autoranging Digital Multimeter

EASTCO LIMITED 儀 高 儀 器 有 限 公 司



香港總公司
香港新界荃灣沙咀道26-38號
匯力工業中心2字樓26室
電話: (852)2456 1823
傳真: (852)2469 1767
電郵: info@eastco-hk.com
網址: <http://www.eastco-hk.com>
網絡實名: 儀高南儀器

中國公司
儀高南儀器(深圳)有限公司
中國深圳市八卦四路素泰克大廈
3樓V區 郵編: 518029
電話: (86-755) 8241 3890
傳真: (86-755) 8241 3857
電郵: shenzhen@eastco-hk.com

上海辦事處
中國上海市滬太路701號
18樓1810室
郵編: 200072
電話: (86-21) 5653 6311
傳真: (86-21) 5653 6309
電郵: shanghai@eastco-hk.com