

# 30A True RMS Mini AC/DC Clamp+ DMM

High Precision to 0.1mA AC or 1mA DC



## Features

- True RMS AC current and voltage
- Measure low current with high resolution to 0.1mA AC or 1mA DC
- Large 4000 count LCD display with full function indication
- Fast 40 segment analog bargraph
- One touch "Auto Zero" for DCA measurements eliminates the need to turn a knob to zero adjust
- Data hold, Max/Min recall display and auto power off
- 0.9" (23mm) clamp jaw opening, (AWG 1)
- Complete with case, test leads, wrist strap, and 2 AA batteries

Specifications	Range	Resolution	Accuracy(%rdg+digits)	Overload Protection
DC Current	0-4A	1mA	$\pm(1.5\%+3d)$	40A DC
	0-30A	10mA	$\pm(1.5\%+3d)$	100A DC
AC Current (40Hz-1kHz)	0-400mA	0.1mA	$\pm(1.5\%+5d)@50/60Hz$	40A AC
	0-4A	1mA	$\pm(1.5\%+5d)@50/60Hz$	40A AC
	0-30A 0.1mA	10mA	$\pm(2.0\%+5d)@50/60Hz$	100A AC
DC Voltage:	0-400V	0.1V	$\pm(1.0\%+2d)$	1000V DC
AC Voltage:	0-400V	1V	$\pm(1.5\%+3d)$	800V AC
Dimensions/Weight:	7x1.8x1.3" (178x45x32mm) / 8 oz (225g)			

380942 ..... 30A True RMS Mini AC/DC Clamp DMM

**EASTCO LIMITED 儀 高 儀 器 有 限 公 司**



香港總公司  
香港新界荃灣沙咀道26-38號  
匯力工業中心2字樓26室  
電話: (852)2456 1823, 2456 1842  
傳真: (852)2469 1767, 8148 6856  
電郵: info@eastco-hk.com  
網址: <http://www.eastco-hk.com>  
網絡實名: 儀高儀器

中國公司  
儀高南儀器(深圳)有限公司  
中國深圳市八卦四路泰克大廈  
3樓V區 郵編: 518029  
電話: (86-755) 8241 3890  
傳真: (86-755) 8241 3857  
電郵: shenzhen@eastco-hk.com

上海辦事處  
中國上海市滬太路701號  
18樓1810室  
郵編: 200072  
電話: (86-21) 5653 6311  
傳真: (86-21) 5653 6309  
電郵: shanghai@eastco-hk.com