

Pocket LCR Meter

3-1/2 Digit LCD Displays Inductance, Capacitance, and Resistance

Features :

- 1999 count 0.5" LCD display
- Wide inductance (L), Capacitance (C), and Resistance (R) ranges
- Small size, fits in a pocket
- Overrange indication
- Complete with 9V battery and test leads



Specifications

| | Range | Max. Resolution | Accuracy(%rdg+digits) |
|-----------------|----------------------------|-----------------|-----------------------|
| Inductance: | 2mH-20H | 1mH | ±(5%+5d) |
| Capacitance: | 2nF to 200μF | 1pF | ±(3%+3d) |
| Resistance: | 200Ω to 20MΩ | 0.1Ω | ±(2%+3d) |
| Test Frequency: | 250Hz | | |
| Dimensions: | 4.7x2.8x1.5" (120x72x37mm) | | |
| Weight: | 7oz. (186g) | | |

381820 LCR Meter

EASTCO LIMITED 儀 高 儀 器 有 限 公 司



香港總公司
匯力工業中心2字樓26室
電話: (852)2456 1823
傳真: (852)2469 1767
電郵: info@eastco-hk.com
網址: <http://www.eastco-hk.com>
網絡實名: 儀高南儀器

中國公司
儀高南儀器(深圳)有限公司
中國深圳市八卦四路素泰克大廈
3樓V區 郵編: 518029
電話: (86-755) 8241 3890
傳真: (86-755) 8241 3857
電郵: shenzhen@eastco-hk.com

上海辦事處
中國上海市滬太路701號
18樓1810室 郵編: 200072
電話: (86-21) 5653 6311
傳真: (86-21) 5653 6309
電郵: shanghai@eastco-hk.com