

EMF Multimeter Adaptor

Permits any DMM to display (0.1 to 199.9) milliGauss or (0.01 to 19.99) microTesla

Features :

- Direct reading of Electromagnetic field (EMF) on DC mV range of any multimeter or voltage recorder/datalogger
- Outputs 1.0mV dc for each milliGauss (0.1 u Tesla) unit
- Remote probe provides single axis measurements with 30 to 300Hz operational bandwidth
- 4% basic measurement accuracy at 50/60-Hz
- Includes remote probe, 36" (0.9m) cable, and 9V battery



Specifications

Measurement Range:	0.1 to 199.9 milliGauss (0.01 to 19.99 mTesla)
ELF Frequency Range:	30 to 300 Hz
Accuracy:	±(4% output + 2mV) at 50/60Hz
Output:	1mV dc per 1 milliGauss (0.1 mTesla)
Dimensions:	3.9x2.0x1.0" (100x50x25mm) Probe:6.9x1.8x0.9" (175x45x22mm)
Weight:	7.3oz. (206g)

480824 EMF Multimeter Adaptor

EASTCO LIMITED 儀 高 儀 器 有 限 公 司



香港總公司
香港新界荃灣沙咀道26-38號
匯力工業中心2字樓26室
電話: (852)2456 1823
傳真: (852)2469 1767
電郵: info@eastco-hk.com
網址: <http://www.eastco-hk.com>
網絡實名: 儀高南儀器

中國公司
儀高南儀器(深圳)有限公司
中國深圳市八卦四路泰克大廈
3樓V區 郵編: 518029
電話: (86-755) 8241 3890
傳真: (86-755) 8241 3857
電郵: shenzhen@eastco-hk.com

上海辦事處
中國上海市滬太路701號
18樓1810室
郵編: 200072
電話: (86-21) 5653 6311
傳真: (86-21) 5653 6309
電郵: shanghai@eastco-hk.com